

# Maintenance Guidelines

## General

- Check if product works correctly.
- Check all bolts and nuts, tighten if needed.
- Check device for stability.
- Check safety of the surface.
- Register all inspections and maintenance.

## Fasteners

- at least 2x a year
- Fasteners like bolts, nuts, washers etc. must be replaced immediately when damaged or worn.

## Bearings/gears/springs/drive belts

- at least 2x a year
- Check gears. Take away backlash if needed.
  - Grease bearings/gears with suitable grease.
  - Check springs and drivebelts on deformation and damage. Replace when damaged or worn.

## Chains

- at least 4x a year
- Check chains for damage between links.
  - When a link has worn for over 30%, replace immediately.

## Wood

- at least 6x a year
- Inspect regularly for cracks, tears, splinters and burn marks.
  - Damaged spots need to be scraped out and dried.
  - Retouch the spots, sand them and repaint.

## Plastics/rubbers/moulded resins

- at least 2x a year
- Clean with water or an environmental friendly cleaning detergent.
  - Check for damaged or worn patches. Retouch when possible or replace.

## Steel

- at least 2x a year
- Clean with water or an environmental friendly cleaning detergent.
  - Cracks and rusted steel need to be repaired immediately.
  - Touch up light scratches and corrosion.

## Electrical components

- at least 2x a year
- Check if Human Power supply (generator) runs smoothly.
  - Listen to the speaker sound quality.
  - Check the LED-strips for failures.
  - Check functionality of buttons.
  - Check cables for damages. Replace or fix when damaged.
  - Check plugs for moist and welds. Replace or fix when damaged.
  - Check if the USB-port is covered against moist.
  - Do not worry about moisture between moulded PCB's and PC covers.
  - Update your timelock. Check the User Manual for the instructions.

## Product Specific Maintenance

- AudioSense: replace smell cartridge 4x a year.
- AudioBench: Check stop-block on cracks and damage 3x a year.
- WaterCannon: Unlink water supply and drain before sub-zero temperatures.
- Clean nozzle and filters 3x a year


## User Manuals

Use our products according to the Playnetic User Manuals. For subjects like volume, content and timelock, follow the instructions in these manuals.

## Installation Manuals

Install our products according to the Playnetic Installation Manuals.

Collect your manuals at:  
[www.playnetic.nl/products/](http://www.playnetic.nl/products/)



**playNETIC**  
Human Powered Play